

# Product Detail Page



## CD-112

Number: 21.2800

### CD and MP3 player,

with USB interface and SD/MMC card slot.

- USB storage media can be connected directly
- For SD/MMC cards up to 32GB (FAT16/FAT32), available at option
- Anti-shock system
- Supports ID3 tags
- Autoplay function
- Fast forward and reverse
- Track programming
- Folder navigation
- Repeat function (repeat 1, repeat all, random repeat)
- Random play
- Supplied with infrared remote control
- 482mm (19") rack installation, 1RS
- Audio CD/CD-R/CD-RW/MP3 CD

Also suitable for HiFi and PA applications.

### tastenwelt 05/2011

"Twice as good! With the new CD/MP3 players CD-112 and CD-112TRS from IMG Stage Line, a musician can meet every requirement."

# Technical Facts

## General information

|                                  |                                  |
|----------------------------------|----------------------------------|
| <b>Frequency range</b>           | 20-20,000Hz                      |
| <b>THD</b>                       | < 0.1%                           |
| <b>Channel separation</b>        | > 60dB                           |
| <b>Dynamic range</b>             | > 96dB                           |
| <b>S/N ratio</b>                 | > 70dB                           |
| <b>Wow and flutter</b>           | not measurable, quartz precision |
| <b>Output, analog</b>            | 1.2V                             |
| <b>Output, digital</b>           | -                                |
| <b>Power supply</b>              | 230V~/50Hz/50VA                  |
| <b>Admiss. ambient temp.</b>     | 0-40 °C                          |
| <b>Dimensions, player mech.</b>  | 482x44x265mm, 1RS                |
| <b>Dimensions, control panel</b> | -                                |
| <b>Weight</b>                    | 4kg                              |
| <b>Connections</b>               |                                  |
| <b>Analog output</b>             | 1 x RCA L/R                      |
| <b>Digital output</b>            | -                                |
| <b>Fader start</b>               | -                                |
| <b>Control connection</b>        | -                                |

